

KP-32 Menu System Quick Reference

Menu Access

1. Clear **all names** from the call waiting display (if not clear) by tapping up one or more times on the call waiting key.
2. Tap **MENU** to activate the menu system.
3. Press **↓↓** to scroll forward through the list of menus. Press **↑↑** to scroll back.
4. Tap **FWD** or **PGM** to enter a menu. Tap **BACK** to exit a menu.
5. Within a menu:
 - Press **↓↓** or **↑↑** to scroll.
 - Tap **FWD** or **PGM** to select an item.
 - Tap **BACK** to cancel a selection or to go back to the previous menu level.

Menu List

Display Menu	Key Assign Menu	Key Options Menu	RVON Conn.	Service Menu
Asgn Type	Pt-to-Pt	Auto Dial ¹	list of RVON Offers ¹	Aux Inputs
Chans ON	Party Line	Chime ¹		Baud Rate
Key Groups	IFB	Key Groups ¹		Caller Vol.
Key List	Spcl List	Solo ¹		Dim ¹
Level 2	Sys Relay			Displ Dim ¹
Listen	Camera ISO			DSP Func ¹
Matrix	UPL			Hdst Set ¹
Panel ID	IFSL			LCP-32 ¹
Version	Auto Func			Local GPIO ¹
	Key Gain			Matrix OUT ¹
	Reset Vols			Mic Select ¹
	Setup Page			Min Volume ¹
				Mod Assign ¹
				Outp Level ¹
				Preamp Out ¹
				Reset Cfg
				RVON Setup ¹
				Save Cfg
				Scr Saver ¹
				Sidetone ¹
				Snoop Tally ¹
				Test Panel
				Tone Gen

1. Run Save Cfg (see “Service Menu, Save Cfg” on page 47) to save these settings.